

## **C402W Wireless Solar Powered Security PIR Camera System (VC402+VR131)**

- ü Weatherproof design camera suitable for the location no mains power available
- ü Separate solar panel allow placing at best position to collect sunlight
- ü Built in PIR to detect movement & IR LED to enhance night time vision
- ü High quality microphone gives crystal clear sound transmission
- ü PIR camera connect with PC to make best performance via USB2.0 bus (Win°P)
- ü USB Receiver allow any wireless camera to be recorded to your PC/Laptop when connected  
PIR camera is triggered
- ü Encoding MPEG4 format for video application
- ü Support Brightness, Contrast, Saturation, Sharpness, Snapshot

### **Specification**

Model No.	VC402
Model Name	Wireless Security PIR camera
Frequency Range	2.400~2.483GHz
Image sensor	1/3" Colour CMOS
Resolution	NTSC 510*492 / PAL 628*582
Use Location	Outdoor
Channel	4
Operation Range	100M
Image sensor	1/3" Colour CMOS
PIR coverage	80-degree x 8M
Protection Level	IP44
Power	Solar power
Battery	9V Alkaline battery *1 & 6V/1.2AN Rechargeable battery
Compatibility	CA117, VR111, VR131

### **Specification**

Model No.	VR131
Model Name	Wireless USB Receiver
Frequency Range	2.400~2.483GHz

Channel	4
Video Encoding Format	MPEG 4
Operation Range	100M
Power	USB Input DC5V, 500mA, or AC120V / 7.5VDC 1A (American) / AC230V / 7.5VDC 1A (European)
Screen view size	50%, 75%, 100%, 200%, Full screen
System requirement	<ul style="list-style-type: none"> <li>1 USB 2.0 equipped computer</li> <li>1 Pentium III 1.5G or above</li> <li>1 128MB RAM</li> <li>1 Windows 2000/°P</li> <li>1 Sound Card</li> <li>1 Direct °9.0C</li> </ul>
Compatibility	VC402, CC425 CC128, VC451

**Standard Package includes :**

- 1\* VC402 Wireless security PIR camera with solar panel
- 1\* VR131 Wireless Recordable Audio/Video Receiver
- 1\* Adaptor (for VR131)
- 1\* USB cable
- 1\*9V Alkaline battery & 1\*6V/1.2AH Rechargeable battery
- Software CD, Fixing and Instruction manual