

## **C451x Wireless Solar Powered Security PIR Camera System (VC451+VR111+SR103)**

- ü Weatherproof design solar powered camera suitable for the location no mains power available
- ü Built in PIR to detect movement & IR LED to enhance night time vision
- ü Built in Receiver to receive command send from the couple SR103 remote control
- ü High quality microphone gives crystal clear sound transmission
- ü Recordable Audio/Video Receiver unit offers clear image with your home TV and auto record when PIR is triggered
- ü Trigger sound, Dwell time, Auto scanning function for selection
- ü Couple with SR103 remote control to view the camera image from TV as your wish

### **Specification**

Model No.	VC451
Model Name	Wireless Solar Powered Security PIR camera
Transmitter Frequency	2.400~2.483GHz
Receiver Frequency	433MHz (EU) / 315MHz (US)
Image sensor	1/3" Color CMOS
Resolution	NTSC 510*492 / PAL 628*582
Use Location	Outdoor
Channel	4
OperationRange	100M
Image sensor	1/3" Color CMOS
PIR coverage	80-degree x 8M
Protection Level	IP44
Power	Solar power
Battery	9V Alkaline battery *1 & 6V/1.2AN Rechargeable battery
Compatibility	VR111
Remote Control	Couple with SR103 remote control to view the camera image from TV Available 433MHz (EU) and 315MHz (US)

### **Specification**

Model No.	VR111
Model Name	Wireless Recordable Audio/Video Receiver

FrequencyRange	2.400~2.483GHz
Channel	4
Dwell time	5/10/15/25 sec.
OperationRange	100M
Display Type	AV Out
Power	DC9V, 500mA
Compatibility	VC402, CC425, CC128, VC451

**Standard Package includes :**

- 1\* VC451 Wireless solar powered security PIR camera
- 1\* VR111 Wireless Recordable Audio/Video Receiver
  - 1\* SR103 remote control
  - 1\* Adaptor (for VR111)
- 1\* RCA or SCART to RCA cable
- 1\*1.5m extension IR LED cable
- 1\* 1\*3V CR2032 battery & 9V Alkaline battery & 1\*6V/1.2AH Rechargeable battery
- Fixing and Instruction manual